END

FILMED

DTIC

MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963-A

National
Defence

Défense
nationale

TAPTRN - A TAPE UTILITY PROGRAM

by

S. Silan

DTIC
S ELECTE D
FEB 2 5 1985
E

DEFENCE RESEARCH ESTABLISHMENT OTTAWA
TECHNICAL NOTE 83-38

Canada

April 1984
Ottawa

85 02 05 057

National Défense
Defence nationale

TAPTRN - A TAPE UTILITY PROGRAM

by

S. Slinn
SARSAT Project
Electronics Division

DEFENCE RESEARCH ESTABLISHMENT OTTAWA
TECHNICAL NOTE 83-38

ABSTRACT

        The computer program TAPTRN, a utility routine used to read
magnetic tapes of unknown content and format, is described for use on an
HP 1000 computer. It provides the user ready access to all the capabilities
of the tape handling hardware of the HP 1000. TAPTRN is documented in terms
of a brief description of the utility, its capabilities, a guide on how to
use it, and the source and pseudocode for the routines written.

RÉSUMÉ

        Cet ouvrage porte sur le programme d'ordinateur TAPTRN, sous-
programme de service utilisé avec l'ordinateur HP 1000 pour lire des bandes
magnétiques de présentation et de contenu inconnus. Ce programme permet à
l'utilisateur d'avoir facilement accès à toutes les possibilités du
dérouleur de bande de l'ordinateur HP 1000. L'auteur fait une brève
description du sous-programme de service TAPTRN, explique quelles sont ses
possibilités, fournit des instructions sur la façon de l'utiliser et indique
la source et le pseudo-code des routines écrites.

TABLE OF CONTENTS

1.0 INTRODUCTION

TAPTRN is a utility program to aid in the processing of digital tapes.

This report describes two programs, TAPTRN and TSTAPE. TAPTRN is a FORTRAN callable subroutine designed to facilitate the processing of digital tapes. It contains a variety of functions which makes available all the capabilities of the mag tape hardware. This subroutine is written in FORTRAN 4X and FLECS, a FORTRAN preprocessor.

TSTAPE is a main program, written in FORTRAN 4X, that has been created to facilitate the usage of the TAPTRN program by providing full access to all the TAPTRN functions.

Both of the programs, TAPTRN and TSTAPE, are intended to be used on an HP1000 computer with a RTE IVB operating system.

In the following sections, TAPTRN will be documented under the headings: Program Overview, Calling Sequence and Parameter List, and Error Codes. The source listing for TAPTRN is found in Appendix A and the pseudo code describing the source listing in Appendix B. TSTAPE will be documented under the headings: Program Overview, and Compiling and Running the Program. The source listing for TSTAPE is found in Appendix C and the pseudo code describing the source listing in Appendix D.

2.0 TAPTRN DESCRIPTION

2.1 PROGRAM OVERVIEW

The facilities provided by TAPTRN are as follows:

1) Variable record length.

2) Ability to skip and backspace multiple records or files, thereby allowing the user to:

a) skip to subsequent files without having to read through intervening files;

b) position the tape at the logical end of volume;

c) perform a logical rewind to position the tape at the beginning of a file which is not the first file on the reel.

3. Provide the calling program with information on the tape position, i.e. BOT, EOF.

4. Return success or failure on all requested functions along with device status word.

5. Erase four inches of tape.

TAPTRN has ten different functions. With this capability, the user has all the necessary functions to perform any combination of operations on the tape drive. The only restrictions imposed are those of the hardware limitations of the controller and drive.

2.2 CALLING SEQUENCE AND PARAMETER LIST

TAPTRN is called by the FORTRAN statement:

CALL TAPTRN(IUNIT,KODE,KOUNT,IERR,NTRAN,IPOS,ISTAT,IBUFF)

None of these parameters are optional, however, some of the parameters are for input, and some are for output. The input parameters are:

IUNIT – the logical unit number assigned to the tape drive, it has to be zero (not related to the system logical unit numbers).

KODE – the function code.

KOUNT – the count, used in combination with KODE as shown in the table for TAPTRN function codes.

IBUFF – the user buffer name, an integer array to receive the data read from the tape, or it contains the data to be written to the tape. The maximum length allowed for this buffer is 9950 words.

The output parameters are:

IERR – the error code, where:

           0 - successful completion of the requested operation
          <0 - failure of requested operation.

IPOS   - the tape position, where:

           =1, BOT
           =2, EOF
           =3, EOT
           =4, EOV

ISTAT - status return information (see table).

NTRAN - for reading/writing records, it contains the actual number of words transferred (in reading, this may differ from KOUNT if an EOF is encountered). For the skip/backspace functions, NTRAN contains the number of files/records skipped.

TABLE 1

TAPTRN Function Codes

KODE	Function
-2	Unlock logical unit
-1	Obtain resource number and lock logical unit
0	Status request
1	Rewind tape
2	Write end-of-file
3	Skip KOUNT records forwards
4	Backspace KOUNT records
5	Skip KOUNT files forwards
6	Backspace KOUNT files
7	Erase four inches of tape
8	Read a record and transfer up to KOUNT words (maximum 500 words)
9	Write a record KOUNT words long (maximum 500 words)

TABLE 2

Status Return Information (ISTAT)

ISTAT	Meaning
1	Parity and/or timing error.
2	Reel does not have Write enable ring.
3	I/O request requested:
	a) Tape motion required, but tape is at load point.
	b) Backward tape motion required, but tape is at load point.
	c) Write request was given, but reel does not have write enable ring.
4	Timing error on last read/write operation.
5	End-of-tape marker sensed.
6	Start-of-tape marker sensed.
7	End-of-file record encountered when reading, forward spacing, or backward spacing.
8	Unit available for use.
9	Unit disabled.
10	Unit currently in operation.
11	Unit waiting for an available DMA channel.

2.3 ERROR CODES

TAPTRN carried out a number of checks on the input parameter list to ensure valid requests. The code placed in IERR is generated by TAPTRN and not by the operating system. The error codes which can be set by TAPTRN are listed below.

TAPTRN Error Codes (IERR)

<u>Code</u>	<u>**Description**</u>	<u>**Source**</u>
-2	Invalid function code.	KODE out of range (-2 to 9).
-37	No file accessed on logical unit number.	Logical unit was not locked.
-92	Invalid logical unit.	Logical unit number was not zero.
-93	Logical unit was not unlocked.	Specified logical unit not in SST.

3.0 <u>TSTAPE DESCRIPTION</u>

3.1 PROGRAM OVERVIEW

TSTAPE has been created to (a) facilitate the usage of the TAPTRN program and (b) be used as an aid in the analysis of computer tapes of unknown format. TSTAPE has many commands which provide full access to all the TAPTRN functions. These are as follows:

```
COMMAND SUMMARY (X=UNIT,DEFAULT=0)

IN(X) = INITIALIZE THE DRIVE (-****MUST BE FIRST COMMAND INPUT****)
RD(X) = READ A RECORD
WT(X) = WRITE A RECORD
DI    = DISPLAY A READ/WRITE BUFFER
ST    = DRIVE STATUS (LAST COMMAND)
SL    = SET RECORD LENGTH
RW(X) = REWIND TAPE
NR(X) = NUMBER OF RECORDS IN THE FILE
SK(X) = SKIP
RL(X) = FIND THE RECORD LENGTH (WORDS)
EF(X) = WRITE AN EOF
TS(X) = WRITE/READ TEST
SH    = SHOW THE FIRST RECORD OF EACH FILE ON THE TAPE
EX    = EXIT
HE    = HELP
```

When first using this tape package, the most helpful command is HE, the help command. This command will display the command summary shown above, on the screen.

The commands are self explanatory but a few will be expanded upon here. It should be noted that the first command that should be input is IN(X), initialize the drive. If another command is input first, before this one, an error message will appear stating that the drive has not been initialized. This command has been incorporated to accommodate multiple tape drives on the system, allowing the user to acquire one drive solely for their use.

The command DI, Display the Read/Write Buffer, has the capability to display the buffer in ASCII, integer or octal format, and to convert EBCDIC and BCD data to ASCII before displaying. The user will be queried which of these capabilities is to be utilized at the appropriate time.

For all the commands that have (X) included in them, i.e. IN(X), it is not necessary to include the (X) with the command if the user wishes to use the unit default of 0. For example, instead of entering RD(0), the user can enter RD.

3.2 COMPILING AND RUNNING THE PROGRAM

In order to run this program, enter the following command while in file manager:

:RU,TSTAPE

The initial screen display introducing the program will then appear.

Command files have been created in case it is necessary to re-compile and load the program. A listing of these command files is found in Appendix E. The rebuilding of the program is done in two stages. First invoke the transfer file, RTAPE, by entering:

:TR,RTAPE

in order to rebuild the TAPTRN program. Then, invoke the transfer file, CTSTAP, by entering:

:TR,CTSTAP

in order to rebuild the TSTAPE program and to link and load the TSTAPE and TAPTRN programs together. The program TSTAPE, is then ready to run in the manner stated above.

4.0 <u>SUMMARY COMMENTS</u>

This report has described the two programs, TSTAPE and TAPTRN. TSTAPE has been described along with a description of how to compile and run the program. TAPTRN has been described along with a description of its parameter list, error codes and status return information. Further documentation of each program is provided in the comments of the program.

APPENDIX A

TAPTRN SOURCE LISTING

```
C*********************************************************************
C This is a FORTRAN callable subroutine that is designed to give
C the user the capability to manipulate the tape drive in order
C to read any type of tape.
C The facilities provided by TAPTN are:
C 1)Variable record length
C 2)Ability to skip and backspace multiple records or files
C    thus permitting the user to:
C       a)skip to subsequent files without having to read through
C           intervening files
C       b)position the tape at the logical end of volumne
C       c)perform a logical rewind to position the tape at the
C           beginning of a file which is not the first file on the reel
C       d)provide the calling program with information on the tape
C           position eg.BOT,EOF
C       e)allow tape formatting eg.writing EOF,EOV
C       f)return success or failure on all requested functions along
C           with device status word
C       g)erase four inches of tape
C
C The calling sequence to invoke this subroutine is:
C
C    CALL TAPTN(IUNIT,KODE,KOUNT,IERR,NTRAN,IPOS,ISTAT,IBUFF)
C
C See the program documentation for a description of the parameters.
C
C The files used with this program are:
C    &TAPTRN -source module
C    %TAPTRN -relocatable module
C    TAPTN   -runnable program
C    RTAPE   -transfer file to compile TAPTN
C    -note- all these files reside on cartridge 13
C
C To create this subroutine invoke the transfer file, RTAPE by,
C    :TR,RTAPE
C
```

```
C Author: Suzanne Slinn
C Date: November 6,1982
C
C*********************************************************************
C
C
$FILES(15,15)
      SUBROUTINE TAPIN(IUNIT,KODE,KOUNT,IERR,NTRAN,IPOS,ISTAT,IBUFF)
      INTEGER IERR,ISTAT,KODE,IUNIT,ICON,LURAY(6),NUM,I,ITOPE,ICNWD,
     1       ISTA1,LUN,IA,IR,IN,OUT,TYPE,IBUFL,ITEST,IBUFF(9950)
      LOGICAL FOUND,EOF,EOT,ILOCK
      DATA IN/1/,OUT/1/,ILOCK/.FALSE./
C
C     Initialize error codes
      IERR=-2
      ISTAT=0
      NTRAN=0
      ISTA1=0
      IPOS=0
C
C     Check for valid function code
      IF ((KODE .LT. -2) .OR. (KODE .GT. 9)) RETURN
C
C     Check if Magtape unit number valid
      IERR=-92
      IF (IUNIT .NE. 0) RETURN
      LUN=IUNIT+8
      IERR=-37
      IF (KODE .GE. 0)
     1    IF (.NOT.(ILOCK)) RETURN
      FIN
      IERR=0
```

12

```
C
C     Case Function Code of
      SELECT (KODE)
      (-2)
C        Unlock
         ICON=0000000B
         NUM=1
         LURAY(1)=LUN
C        Unlock the LU
         CALL LURQ(ICON,LURAY,NUM)
         ILOCK=.FALSE.
         RETURN
         FIN
C
      (-1)
C        Lock
         ICON=0000001B
         NUM=1
         LURAY(1)=LUN
C        Lock the LU
         CALL LURQ(ICON,LURAY,NUM)
         ILOCK=.TRUE.
         RETURN
         FIN
C
      (0)
C        Status request
         ICNWD=0
         ICNWD=ICNWD+8
         CALL EXEC(13,ICNWD,ISTA1)
         CALL STATS(ISTA1,ISTAT)
         IERR=0
         RETURN
         FIN
C
```

```
C           Rewind tape
   (1)      CALL MANIP(4,LUN)
            CALL EXEC(13,LUN,ISTAT)
            CALL STWAT(ISTAT)
            ISTAT=0
            IPOS=1
            IERR=0
            RETURN
            FIN
C
C           Write end of file
   (2)      CALL MANIP(1,LUN)
            CALL EXEC(13,LUN,ISTAT)
            CALL STWAT(ISTAT)
            ISTAT=0
            IERR=0
            IPOS=2
            RETURN
            FIN
C
C           Skip KOUNT records forwards
   (3)
```

```
C
      I=1
      EOF=.FALSE.
      WHILE ((I .LE. KOUNT) .AND. (.NOT. (EOF)))
C       Forward space 1 record
        CALL MANIP(3,LUN)
        ICNWD=8
        CALL EXEC(13,ICNWD,ISTA1)
        CALL STWAT(ISTA1)
        ITEST=IAND(ISTA1,(2**7))
        WHEN (ITEST .EQ. 2**7)
          EOF=.TRUE.
          ISTAT=7
          IPOS=2
          I=I-1
        FIN
        ELSE.
          ITEST=IAND(ISTA1,(2**5))
          IF (ITEST .EQ. (2**5))
            EOF=.TRUE.
            ISTAT=5
            IPOS=3
            I=I-1
          FIN
        FIN
        I=I+1
      FIN
      WHEN (I .GT. KOUNT)
        NTRAN=I-1
      FIN
      ELSE.
        NTRAN=I
      FIN
      IERR=0
      RETURN
      FIN
C
```

```
(4)
C      Skip KOUNT records backwards
       I=1
       EOF=.FALSE.
       WHILE (( I .LE. KOUNT) .AND. (.NOT. (EOF)))
C          Backward space 1 record
           CALL MANIP(2,LUN)
           ICNWD=8
           CALL EXEC(13,ICNWD,ISTA1)
           CALL STWAT(ISTA1)
           ITEST=IAND(ISTA1,(2**7))
           WHEN (ITEST .EQ. 2**7)
               EOF=.TRUE.
               ISTAT=7
               IPOS=2
               I=I-1
           FIN
           ELSE
               ITEST=IAND(ISTA1,(2**6))
               IF (ITEST .EQ. (2**6))
                   EOF=.TRUE.
                   ISTAT=6
                   IPOS=1
                   I=I-1
               FIN
           FIN
           I=I+1
       FIN
       WHEN (I .GT. KOUNT)
           NTRAN=I-1
       FIN
       ELSE
           NTRAN=I
       FIN
       IERR=0
       RETURN
       FIN
C
```

16

```
C       Skip KOUNT files forwards
(5)     I=1
        EOT=.FALSE.
C       WHILE ((I .LE. KOUNT) .AND. (.NOT. (EOT)))
            Forward space a file
            CALL MANIP(13B,LUN)
            ICNWD=8
            CALL EXEC(13,ICNWD,ISTA1)
            CALL STWAT(ISTA1)
            ITEST=IAND(ISTA1,(2**5))
            IF (ITEST .EQ. 2**5)
                IPOS=3
                EOT=.TRUE.
                ISTAT=5
                I=I-1
            FIN
            I=I+1
        FIN
        IERR=0
        WHEN (I .GT. KOUNT)
            NTRAN=I-1
        FIN
        ELSE
            NTRAN=I
        FIN
        RETURN
C       FIN
```

```
C       Skip KOUNT files backwards
        I=1
        EOT=.FALSE.
        WHILE ((I .LE. KOUNT) .AND. (.NOT. (EOT)))
C           Backward space a file
            CALL MANIP(14B,LUN)
            ICNWD=8
            CALL EXEC(13,ICNWD,ISTA1)
            CALL STWAT(ISTA1)
            ITEST=IAND(ISTA1,(2**6))
            IF (ITEST .EQ. 2**6)
                IPOS=1
                EOT=.TRUE.
                ISTAT=6
                I=I-1
            FIN
            I=I+1
        FIN
        IERR=0
        WHEN (I .GT. KOUNT)
            NTRAN=I-1
        FIN
        ELSE
            NTRAN=I
        FIN
        RETURN
        FIN

C
C (7)    Erase four inches of tape
        CALL MANIP(12B,LUN)
        CALL EXEC(13,LUN,ISTAT)
        CALL STWAT(ISTAT)
        IERR=0
        RETURN
        FIN
C
```

```
C
      (8)   Read a record
            ICODE=1
            ICNWD=8
            IBUFL=KOUNT
            CALL EXEC(ICODE,ICNWD,IBUFF,IBUFL)
            CALL ABREG(IA,IB)
            NTRAN=IB
            CALL STATS(IA,ISTAT)
            IF (ISTAT .EQ. 7)IPOS=2
            IERR=0
            RETURN
            FIN
C
      (9)
C
            Write a record
            ICODE=2
            ICNWD=8
            IBUFL=KOUNT
            CALL EXEC(ICODE,ICNWD,IBUFF,IBUFL)
            CALL ABREG(IA,IB)
            CALL STATS(IA,ISTAT)
            IERR=0
            RETURN
            FIN
      FIN
      RETURN
      END
C**************************************************************************
C
C     This subroutine continually polls the status of the operation
C     until the current operation is complete.
C**************************************************************************
C
C
```

```fortran
      SUBROUTINE STWAT(ISTAT)
      INTEGER ISTAT
15    CONTINUE
      ITEST=(ISTAT .AND. 32768)
      IF (ITEST .EQ. 0) RETURN
      CALL EXEC(13,8,ISTAT)
      GO TO 15
      END
C
C
C*********************************************************************
C     This subroutine performs the I/O control calls such as rewind,
C     write end of file.
C*********************************************************************
C
C
      SUBROUTINE MANIF(FUNC,LUN)
      INTEGER FUNC,LUN,ICNWD
      ICNWD=0
C     Shift the function code six bits to the left in ICNWD
      ICNWD=ICNWD+ISHFT(FUNC,6)
      ICNWD=ICNWD+LUN
      CALL EXEC(3,ICNWD)
      RETURN
      END
C
C
C*********************************************************************
C     This subroutine sets the appropriate bits in ISTAT for status
C     return information.
C*********************************************************************
C
C
      SUBROUTINE STATS(ISTA1,ISTAT)
      INTEGER CHECK,ISTAT,I,ISTA1
      LOGICAL FOUND
      CHECK=0
C     Set the 14 and 15 bits to 1 in CHECK
```

```
      CHECK=CHECK+16384
      CHECK=CHECK+32768
C     Save bits 14 and 15
      CHECK=IAND(CHECK,ISTA1)
C     no bits set
      IF (CHECK .EQ. 0) ISTAT=8
C     14 bit set
      IF (CHECK .EQ. 16384) ISTAT=9
C     15 bit set
      IF (CHECK .EQ. 32768) ISTAT=10
C     14 and 15 bit set
      IF (CHECK .EQ. 49152) ISTAT=11
      I=1
      FOUND=.FALSE.
C     Find the STATUS bit set for bits 1-7
      WHILE (( I .LE. 7) .AND. (.NOT. (FOUND)))
         CHECK=0
         CHECK=IAND(ISTA1,(2**I))
         IF (CHECK .EQ. 2**I))
            ISTAT=I
            FOUND=.TRUE.
         FIN
         I=I+1
      FIN
      RETURN
      END
```

APPENDIX B

PSEUDOCODE

Subroutine TAPTRN

```
    Initialize error codes and other variables

    If (Kode < -2  or Kode > 9)

    then

        Return indicating KODE range error

    endif

    If (Iunit ≠ 0)

    then

        Return indicating invalid logical unit number error

    endif

    If (Kode ≥ 0 and unit not locked)

    then

        Return indicating resource not locked error

    endif

    Case Function Code of

        -2: Unlock the logical unit
            Set locked flag to false
            Return

        -1: Lock the logical unit
            Set locked flag to true
            Return
```

22

```
0: Obtain present drive status
   Set ISTAT to reflect status
   Return

1: Manipulate the bits for rewind code
   Obtain present driver status
   Wait until the driver is available for use
   Return

2: Manipulate the bits for end-of-file code
   Obtain present driver status
   Wait until the driver is available for use
   Return

3: Initialize loop counters
   While (record counter < KOUNT and NOT(EOF))

        Manipulate bits to space 1 record forwards
        Obtain present driver status
        Wait until device is ready for use
        If end of file record bit is set
        then

             EOF = True
             Set ISTAT to reflect EOF
             Set IPOS to reflect EOF
             Decrement record counter

        Else
        If end-of-tape marker bit is set
        then

             EOT = True
             Set ISTAT to reflect EOT
             Set IPOS to reflect EOT
             Decrement record counter

        endif
        Increment record counter

   Endwhile
   If (Record counter > KOUNT)

             NTRAN = record counter-1

   else

             NTRAN = record counter

   endif
   Return
```

```
4: Initialize loop counters
   While (Record counter ≤ KOUNT and NOT(EOF))

        Manipulate bits to backspace one record
        Obtain present driver status
        Wait until device is ready for use
        If end of file record bit is set
        then

             EOF = True
             Set ISTAT to reflect EOF
             Set IPOS to reflect EOF
             Decrement record counter

        else
        If start of tape marker bit is set
        then
             EOF = True
             Set ISTAT to reflect BOT
             Set IPOS to reflect BOT
             Decrement record counter
        endif
        endif
   Endwhile
   If (Record counter > KOUNT)
   then

        NTRAN = record counter-1

   else

        NTRAN = record counter

   endif
   Return

5: Initialize loop counters
   While (Record counter ≤ KOUNT and NOT (EOT))

        Manipulate bits for forward space one file
        Obtain present driver status
        Wait until device is ready for use
        If end-of-tape marker bit is set
        then

             EOT = True
             Set ISTAT to reflect EOT
             Set IPOS to reflect EOT
             Decrement record counter

        endif
        Increment record counter

   Endwhile
   If (Record counter > KOUNT)
   then

        NTRAN = record counter-1
```

24

```
            else

                NTRAN = record counter

            endif
            Return

    6:  Initialize loop counters
        While (Record counter ≤ KOUNT and NOT (EOT))

                Manipulate bits to backspace one file
                Obtain present driver status
                Wait until device is ready for use
                If start-of-tape marker bit is set
                then

                        EOT = True
                        Set ISTAT to reflect EOT
                        Set IPOS to reflect EOT
                        Decrement record counter

                endif
                Increment record counter

        Endwhile
        If (Record counter > KOUNT)
        then

            NTRAN = record counter-1

        else

            NTRAN = record counter

        endif
        Return


    7:  Manipulate bits to erase four inches of tape
        Obtain present driver status
        Wait until device is ready for use
        Return

    8:  Read the record
        Determine the present driver status
        Return

    9:  Write the record
        Determine the present driver status
        Return

End Case on Function Code
Return
End Subroutine TAPTRN
```

Subroutine STWAT

```
c   Subroutine to wait for driver to be ready for use
    While driver not available for use

        Obtain present driver status

    Endwhile
    Return

End Subroutine STWAT
```


Subroutine MANIP

```
c   Subroutine to manipulate bits for desired function code

        Shift function code six bits to the left in ICNWD
        Add the logical unit number to ICNWD
        Perform the function

    Return

End Subroutine MANIP
```


Subroutine STATS

```
c   Subroutine to set appropriate bits in ISTAT to reflect
c   present driver status

        If neither the 14th nor 15th bits in driver status are set
        then

            ISTAT=8

        If 14th bit set in driver status
        then

            ISTAT=9

        If 15th bit set in driver status
        then

            ISTAT=10

        If 14th and 15th bits are set in driver status
        then

            ISTAT=11
```

```
        Initialize loop counters
        While (Present bit ≤ 7 and NOT FOUND)

           If Present bit in driver status set
           then

               ISTAT = Present bit
               FOUND = True

           endif
           Present bit = Present bit +1

        Endwhile
        Return

End Subroutine STATS
```

APPENDIX C

TSTAPE SOURCE LISTING

```
FTN4,T
C*************************************************************************
C This is a FORTRAN program that has been created to
C (1) facilitate the usage of the TAPTRN program,
C (2) aid in the analysis of computer tape of unknown format.
C
C TSTAPE has several commands which provide full access to all
C the TAPTRN functions.  To obtain a list of the commands, type
C HE in response to the INPUT COMMAND) prompt when the program
C runs.
C
C To invoke this program, type RU,TSTAPE.
C
C The files used with this program are:
C  &TSTAPE -source program
C  ZTSTAPE -relocatable module
C  LTSTAPE -transfer file for LOADR
C  CTSTAPE -transfer file to compile and load TSTAPE
C  -note- all these files reside on cartride 13
C
C To create this program invoke the transfer file,CTSTAP by,
C   :TR,CTSTAPE
C AFTER building the subroutine TAPTRN.
C
C To run this program after invoking the transfer file, CTSTAFE,
C type,
C   :RU,TSTAF.
C
C
C Author: Suzanne Y. Slinn
C Date:   November 6,1982
C*************************************************************************
C
```

```fortran
$FILES(15,15)
      PROGRAM TSTAPE
      INTEGER ECM(2),FM,AIO,ITO,OIO,EAO,RAO,TRO,YES,ICOMD,IR,TT
      INTEGER BF1(120),BF2(120),BF3(240),VT(6)
      INTEGER NAME(40),IBIT(2),ILOCK(2),VOL
      DIMENSION IB1(9950),INIT(2),POSN(5),ICMD(19)
      EQUIVALENCE (BF3,BF1),(BF3(121),BF2),(IB1(1),IBIT(1),IBIT(1))
      DATA ICMD/'IN','SH','RD','WT','DI','ST','SL','CO',
     1          'RW','NR','SK','RL','EF','TS','EX','HE','DU','LE',
     2          'SA'/

      DATA INIT/2*0/
      DATA AIO/'A'/,IIO/'I'/,OIO/'O'/,EAO/'E'/,RAO/'R'/,TRO/'T'/,
     1  YES/'Y'/,IU,KT,IR,NT,IP,IS/6*0/
      DATA VT/015452B,062106B,015510B,015517B,015452B,062105B/
      DATA POSN/' ',' EOT',' EOF',' EOT',' EOV'/
      DATA ILOCK/015554B,015555B/
C
C     Clear the screen, home the cursor, display initial messages.
      WRITE(1,490) (VT(I),I=1,6)
490   FORMAT(6A2,//,' TSTAPE: THIS PROGRAM IS INTENDED AS ',/,
     1  ' A) A TEST PROGRAM FOR THE SUBROUTINE TAPTRN AND ',/,
     2  ' B) A UTILITY PROGRAM TO AID IN THE ANALYSIS OF ',/,
     3  ' COMPUTER TAPES OF UNKNOWN FORMAT.',/,
     4  ' **TYPE (HE)LP TO DISPLAY THE AVAILABLE COMMANDS.')
C
C.....Issue the desired command
C     Move cursor to display line
110   CALL KLOAD(22,0)
      WRITE(1,500)
485   READ(1,485)ICM,ICM(2)
      FORMAT(A2,A1)
      ICL=IC
      IUL=ID
      DO 100 I=1,17
      IF (ICM .EQ. ICMD(I)) GO TO 105
100   CONTINUE
```

```
120   CALL KLOAD(22,0)
      WRITE(1,510)
      CALL TIME
      GO TO 110
C
C     A valid command has been identified
105   IB=BCM(2)
      ID=0
      IF (IB .EQ. 2H0 ) ID=0
      IF (IB .EQ. 2H  ) ID=0
      IF (IB .EQ. 2H1 ) ID=1
      IF ((  ID .LT. 0) .OR.  (ID .GT. 1)) GO TO 120
      IF (ID .EQ. 0) IU=0
      IF (ID .EQ. 1) IU=1
      }..I
C
C     Determine if it is the initialization command or a command
C     that does not determine a previous initialization.
      IF ((IC .EQ. 1) .OR. (IC .GT. 14)) GO TO 125
      IF (INIT(IU+1) .EQ. 1) GO TO 125
      CALL KLOAD(22,0)
      WRITE(1,515)
      CALL TIME
      GO TO 110
C
C     Case command of:
125   CALL KLOAD(22,0)
      WRITE(1,1111)ILOCK(1)
      GO TO (5,10,15,20,25,30,35,40,45,50,55,60,65,70,75,80,85
     1  ,90,95),IC
C
C....*IN*, Initialize tape command
5     CALL TAPTN(IU,-1,KT,IR,NT,IP,IS,IB1)
      INIT(IU+1)=1
      ICL=IC
      IUL=ID
      GO TO 30
```

```fortran
C
C....*SH*, Show the contents of the first record of each file
10    KT=9950
      VOL=0
      CALL KLOAD(22,0)
      WRITE(1,541)
      READ(1,505)FM
      CALL TAPTN(IU,1,KT,IR,NT,IP,IS,IB1)
11    CONTINUE
C     Repeat until EOV is true
      IF (VOL .EQ. 1)GO TO 30
      IP=0
      CALL TAPTN(IU,8,KT,IR,NT,IP,IS,IB1)
      IF ((IP .EQ. 2) .OR. (IP .EQ. 3)) VOL=1
      IF (VOL .EQ. 1) GO TO 30
C     If not end of tape, write out first record of file
      WRITE(18,520)NT
      IF (FM .EQ. AIO)WRITE(18,545)(IB1(I),I=1,NT)
      IF (FM .EQ. IIO)WRITE(18,550)(IB1(I),I=1,NT)
      IF (FM .EQ. OIO)WRITE(18,555)(IB1(I),I=1,NT)
      IF (FM .EQ. EAO)CALL EBCDIC(IB1,NT)
      IF (FM .EQ. BAO)CALL BCD(IB1,NT)
      IP=0
12    CONTINUE
      IF (IP .EQ. 2) GO TO 13
      CALL TAPTN(IU,8,KT,IR,NT,IP,IS,IB1)
      GO TO 12
13    GO TO 11
```

```
C
C......*RDX, Read a record
15      CALL KLOAD(22,0)
        WRITE(1,530)
C       Get the Kount words to be read
        READ(1,525)KT
        IF ((KT .EQ. 0) .OR. (KT .GT. 9950)) KT=9950
        DO 16 I=1,KT
16      IB1(I)=0
C       Read one record of the desired length
        CALL TAPTN(IU,8,KT,IR,NT,IP,IS,IB1)
        IF (IP .EQ. 0) GO TO 14
        CALL KLOAD(22,0)
        WRITE(1,535)
        CALL TIME
14      CALL KLOAD(22,0)
        WRITE(1,635)
635     FORMAT(' DUMP TO LINE PRINTER?  (Y)=YES >_')
C       IO=18
C       KT=NT
C       Determine if dump to line printer desired.
        READ(1,505)BF1(1)
        IF (BF1(1) .EQ. YES) GO TO 24
        GO TO 30
C
C......*WTX Write a record
20      CALL KLOAD(22,0)
        WRITE(1,530)
C       Get number of words to write
        READ(1,525)KT
        IF ((KT .EQ. 0) .OR. (KT .GT. 9950)) KT=9950
        CALL KLOAD(22,0)
        WRITE(1,532)
532     FORMAT(' ENTER POSITION IN BUFFER OF WHERE TO START WRITING)_')
C       Get position in buffer of where to start writing data to
        READ(1,525)ISTRT
        KT=ISTRT-1
```

```fortran
      DO 22 I=1,KT
22      IB1(I)=ISTRT+I
C     Write one record of the desired length
      CALL IAPIN(IU,2,KT,IR,NI,IP,IS,IB1)
      GO TO 30
C
C.... *DI* Display the read buffer
25      IO=1
24      CALL KLOAD(22,0)
      WRITE(1,541)
      READ(1,505)FM
      WRITE(1,1111)ILOCK(2)
      WRITE(1,640)(VT(I),I=1,6)
C
C     Determine which form of output is desired.
      IF (FM .EQ. AIO) GO TO 26
      IF (FM .EQ. IIO) GO TO 27
      IF (FM .EQ. OIO) GO TO 28
      IF (FM .EQ. EAO) GO TO 29
      IF (FM .EQ. BAO) GO TO 31
      IF (FM .EQ. TRO) GO TO 32
      GO TO 120
C
C     Ascii data
26      CALL KLOAD(22,0)
      WRITE(1,650)
      READ(1,505)ICOMD
      IF (ICOMD .NE. YES) GO TO 37
      WRITE(1,640)(VT(I),I=1,6)
      WRITE(IO,545)(IB1(I),I=1,KT)
      IF (IO .EQ. 18) GO TO 30
      GO TO 110
37      LW=40
38      IF (ICOMD .NE. YES)LW=66
      WRITE(1,640)(VT(I),I=1,6)
      WRITE(IO,545) (IB1(I),I=1,NT)
      IF (IO .EQ. 18) GO TO 30
      GO TO 110
```

```
C         Integer data
27        WRITE(IO,550) (IB1(I),I=1,NT)
          IF (IO .EQ. 18) GO TO 30
          GO TO 110
C         Real data
28        WRITE(IO,555) (IB1(I),I=1,NT)
          IF (IO .EQ. 18) GO TO 30
          GO TO 110
C         Ebcidic data
29        CONTINUE
          CALL EBCDC(IB1,KT)
          GO TO 26
C         Bcd data
31        CONTINUE
          CALL BCD(IB1,KT)
          GO TO 26
C         Convert to octal data
32        CONTINUE
C         CALL CONVRT(IB1,KT)
C         WRITE(IO,555)(IB1(I),I=1,KT)
          IF (IO .EQ. 18) GO TO 30
          GO TO 110
C
C....*ST* Status of the drive
30        WRITE(1,1111)ILOCK(2)
          WRITE(1,560)(VT(I),I=1,6),IUL,ICMD(IC),KCODE,KT,NT,
     1         PUSN(IP+1),IR,IS
          GO TO 110
C
C....*SL* Set record length
35        CALL KLOAD(22,0)
          WRITE(1,565)
          READ(1,525)KT
          IF ((KT .EQ. 0) .OR. (KT .GT. 9950)) KT=9950
          GO TO 30
C
40        GO TO 110
```

```
C....
C.... *RW* Rewind tape
45      CALL TAPTN(IU,1,KT,IR,NT,IP,IS,IR1)
        GO TO 30
C
C.... *NR* Get the number of records in a file
50      IF ((IP .EQ. 1) .OR. (IP .EQ. 2)) GO TO 51
        CALL KLOAD(22,0)
        WRITE(1,575)
        CALL TIME
        GO TO 30
C
51      K=0
        KS=KT
        KT=9950
C       Read one record
54      CALL TAPTN(IU,B,KT,IR,NT,IP,IS,IR1)
        IF ((K .EQ. 0) .AND. (IP .EQ. 2)) GO TO 52
        IF (IP .EQ. 2) GO TO 53
        K=K+1
        NTL=NT
        GO TO 54
52      CALL KLOAD(22,0)
        WRITE(1,580)
        CALL TIME
        GO TO 30
53      WRITE(1,1111)ILOCK(2)
        CALL KLOAD(21,0)
C       Write out the number of records found
        WRITE(1,1111)ILOCK(1)
        WRITE(1,585)K,NTL
        CALL TIME
        KT=KS
        GO TO 30
```

```
C
C....*SK* Skip to end of file
55      CALL KLOAD(22,0)
        WRITE(1,625)
        READ(1,505)ICOMD
        IK=3
        IF (ICOMD .NE. YES) IK=5
        CALL KLOAD(22,0)
        WRITE(1,630)
        READ(1,525)KT
        IF (KT .GE. 0) GO TO 56
        IK=IK+1
        KT=-KT
56      CALL TAPTN(IU,IK,KT,IR,NT,IP,IS,IB1)
        GO TO 30
C
C....*RL* Find record length
60      KT=9950
        CALL TAPTN(IU,8,KT,IR,NT,IP,IS,IB1)
        CALL KLOAD(22,0)
        WRITE(1,590)NT
        CALL TIME
        GO TO 30
C
C....*EF* Write end of file
65      CALL TAPTN(IU,2,KT,IR,NT,IP,IS,IB1)
        GO TO 30
C
C....*TS* TEST READ WRITE/READ PATTERN
70      CALL KLOAD(22,0)
        WRITE(1,530)
        READ(1,525)KT
        CALL KLOAD(22,0)
        WRITE(1,600)
        READ(1,605)NW,INC
        CALL KLOAD(22,0)
```

```fortran
      WRITE(1,620)
      READ(1,505)ICOMD
      IF(ICOMD .NE. YES) GO TO 71
      CALL KLOAD(22,0)
      WRITE(1,540)
      READ(1,505)FM
C
71    KT1=KT
      DO 81 I=1,NW
      DO 82 J=1,KT1
      IB1(J)=J
82    IF (ICOMD .NE. YES) GO TO 72
      IF (FM .EQ. AIO)WRITE(18,545)(IB1(L),L=1,KT1)
      IF (FM .EQ. IIO)WRITE(18,550)(IB1(L),L=1,KT1)
      IF (FM .EQ. OIO)WRITE(18,555)(IB1(L),L=1,KT1)
C     Write a record
72    CALL TAPTN(IU,9,KT1,IR,NT,IP,IS,IB1)
      IF (IR .EQ. 0) GO TO 83
      WRITE(1,1111)ILOCK(2)
      WRITE(1,560)(VT(J),J=1,6),IUL,ICMD(ICL),KCODE,KT1,NT,
     1              POSN(IP+1),IR,IS
83    KT1=KT1+INC
      IF ((KT1 .LE. 0) .OR. (KT1 .GT.9950)) GO TO 84
81    CONTINUE
C
C.....Write 2 end of files/rewind and read
84    CALL TAPTN(IU,2,KT,IR,NT,IP,IS,IB1)
      CALL TAPTN(IU,2,KT,IR,NT,IP,IS,IB1)
      CALL TAPTN(IU,1,KT,IR,NT,IP,IS,IB1)
C
      IUL=IU
      KT1=KT
      DO 86 I=1,NW
      DO 89 J=1,KT1
      IB1(J)=0
89
```

```fortran
C         Read a record
          CALL TAPTN(IU,8,KT1,IR,NT,IP,IS,IB1)
          IF (ICOMD .NE. YES) GO TO 73
          IF (FM .EQ. AIO) WRITE(18,545)(IB1(L),L=1,KT1)
          IF (FM .EQ. IIO) WRITE(18,550)(IB1(L),L=1,KT1)
          IF (FM .EQ. OIO) WRITE(18,555)(IB1(L),L=1,KT1)
          IEC=0
          DO 87 J=1,KT1
          IF (IB1(J) .NE. J) IEC=IEC+1
87        CONTINUE
C
          IF (IR .EQ. 0) GO TO 88
          WRITE(1,1111)ILOCK(2)
          WRITE(1,560)(VT(J),J=1,6),IUL,ICMD(ICL),KCODE,KT1,
     1    NT,POSN(IP+1),IR,IS
88        IF (IEC .EQ. 0) GO TO 92
          CALL KLOAD(22,0)
          WRITE(1,610)I,IFC
92        KT1=KT1+INC
          IF ((KT1 .LE. 0) .OR. (KT1 .GT. 9750)) GO TO 110
86        CONTINUE
          CALL TAPTN(IU,1,KT,IR,NT,IP,IS,IB1)
          GO TO 110
C
C.....*EX* Exit
75        WRITE(1,1111)ILOCK(2)
          CALL TAPTN(IU,-2,KT,IR,NT,IP,IS,IB1)
          STOP
C
C.....*HE* Help facility
80        WRITE(1,1111)ILOCK(2)
1111      FORMAT(A2)
          WRITE(1,640)(VT(I),I=1,6)
          OPEN(33,FILE='HELINS',IOSTAT=IOS)
998       CONTINUE
```

```
      READ(33,222,ERR=111,END=111)(BF1(I),I=1,80)
222   FORMAT(80A1)
      WRITE(1,223)(BF1(I),I=1,72)
223   FORMAT(1X,72A1)
      GO TO 998
111   CONTINUE
      CLOSE(33)
      GO TO 110

85    GO TO 110
90    GO TO 110
95    GO TO 110
C
C
C.....Format statements.
500   FORMAT(' INPUT COMMAND >_')
505   FORMAT(2A1)
510   FORMAT(' *INVALID COMMAND*')
515   FORMAT(' *INITIALIZE DRIVE*')
520   FORMAT(' INPUT PARITY (O)DD,(E)VEN >_')
525   FORMAT(I7)
530   FORMAT(' INPUT RECORD SIZE (DEFAULT, KT=9950) >_')
535   FORMAT(' *EOF MARKER READ*')
540   FORMAT(' FORMAT? (A)SCII,(I)NTEG,(O)CTAL,(E)BC OR (B)CD TO ',
     1       ' ASCII >_')
541   FORMAT(' FORMAT? (A)SCII,(I)NTEG,(O)CTAL,(E)BC OR (B)CD TO ',
     1       ' ASCII >_')
545   FORMAT(2X,38A2)
550   FORMAT(12X,8I7)
555   FORMAT(12X,8O7)
560   FORMAT(6A2,//,35X,' TAPE STATUS',//,' UNIT',7X,I6,11X,
     1       'LAST COMMAND',5X,A2,/,' PAR/DENS    ',I6,11X,
     2       'KOUNT',7X,I7,11X,'NTRAN',7X,I7,/,' POSN',9X,A4,11X,
     3       'IERR',8X,I7,11X,'ISTAT',7X,I7)
565   FORMAT(' INPUT KOUNT SIZE(DEFAULT KT=9950 >_')
570   FORMAT(' *ROUTINE NOT WRITTEN*')
575   FORMAT(' *TAPE IS NOT AT BOT OR EOF*')
```

```
 580    FORMAT(' *END OF TAPE*')
 585    FORMAT(' NO. OF RECORDS(EOF EXCLUDED)',I7,/,1X,
        1       ' SIZE LAST DATA RECORD',I7)
 590    FORMAT(' NO. OF WORDS READ=',I7)
 600    FORMAT(' INPUT NO OF RECORDS AND INC/DEC (7 DIGITS) >_')
 605    FORMAT(I7,1X,I7)

 610    FORMAT(' RECORDS NO=',I7,'NO OF READ ERRORS=',I7)
 620    FORMAT(' DO YOU WANT BUFFER DUMPS? (Y)=YES  >')
 625    FORMAT(' RECORD SKIP? (Y)=YES >_')
 630    FORMAT(' INPUT KOUNT,NEGATIVE MEANS BACKSKIP >_')
 640    FORMAT(6A2)
 650    FORMAT(' WITH CARRIAGE CONTROL? (Y)=YES >_')
 655    FORMAT(' TWO LINE WIDTH NOT AVAILABLE')
 660    FORMAT(A2)
 665    FORMAT(' TAPE IS MOUNTED AND DRIVE INITIALIZED? (Y)=YES >_')
 670    FORMAT(' IS SOURCE TAPE ON DRIVE ZERO? (Y)=YES >_')
 675    FORMAT(' DO YOU WANT A CODE CONVERSION? (Y)=YES >_')
 680    FORMAT(' WHICH ONE? (E)BC OR (B)CD TO ASCII? >_')
 685    FORMAT(' DO YOU WANT A MAP DUMP OF THE TAPE? (Y)=YES >_')
 690    FORMAT(6I6)
 695    FORMAT(' DEFAULT MAP IS TO SPOOL? (Y)=YES >_')
 6000   FORMAT(' FILENAME? >_')
 6005   FORMAT(40A1)
 6010   FORMAT(' RECORD SIZE ON OUTPUT (MAX=132)? >_')
 6015   FORMAT(I6)
 6020   FORMAT(132A1)
        END
```

```
C
C THIS SUBROUTINE GETS THE CURRENT SYSTEM TIME
C
      SUBROUTINE TIME
      INTEGER ITIME(5),SEC,DIFF
      CALL EXEC(11,ITIME)
      SEC=ITIME(2)
      DIFF=0
1     CONTINUE
      IF (DIFF .GT. 2) GO TO 2
          CALL EXEC(11,ITIME)
          DIFF=ITIME(2)-SEC
          GO TO 1
2     CONTINUE
      RETURN
      END
```

```
FTN4X,I
C
C
C KLOAD
C
      SUBROUTINE KLOAD(IRL,ICL)
      IMPLICIT REAL*8(A-H,O-Z)
      INTEGER ICA(2),ICB(1),ICC(2),ARAY(24),IC(24)
      DATA ICA/015446B,060400B/
      DATA ICB/071000B/
      DATA ICC/041400B,015512B/
      DO 1 I=1,7
    1 IC(I)=2H
      ENCODE(24,500,IC) (ICA(I),I=1,2),IRL,ICR,ICL,(ICC(I),I=1,2)
  500 FORMAT(2A2,I2,A2,I2,2A2)
      WRITE(1,510)(IC(I),I=1,7)
  510 FORMAT(1X,7A2)
      RETURN
      END
```

```
& EBCDIC
FTN4

C THE FOLLOWING SUBROUTINE ACCEPTS AN ARRAY OF WORDS (MAXIMUM SIZE 9950)
C CODED IN EBCDIC AND CONVERTS EACH WORD TO ASCII CODE.    THE SIZE OF THE
C ARRAY IS PASSED THROUGH PARAMETER "NO" AND THE RESULTANT ASCII CODE IS
C PASSED BACK THROUGH THE PARAMETER "BUFF".

      SUBROUTINE EBCDIC(BUFF,NO)
      INTEGER CD1,CD2
      INTEGER ASC(255),NO,I,TEMP1,BUFF(9950),HIGH,LOW
      DATA ASC/1B,2B,3B,0B,11B,0B,177B,0B,0B,0B,13B,14B,15B,16B,17B,
     1 20B,21B,22B,0B,0B,10B,0B,30B,31B,0B,0B,0B,0B,0B,0B,0B,
     1 0B,0B,34B,0B,12B,27B,33B,0B,0B,0B,0B,5B,6B,7B,
     1 0B,0B,26B,0B,0B,36B,0B,4B,0B,0B,0B,24B,25B,0B,32B,
     1 40B,40B,40B,40B,40B,40B,40B,40B,40B,40B,56B,74B,50B,
     1 53B,174B,46B,40B,40B,40B,40B,40B,40B,40B,40B,40B,
     1 41B,44B,52B,51B,73B,40B,55B,57B,40B,40B,40B,40B,
     1 40B,40B,40B,40B,40B,54B,45B,137B,76B,77B,40B,40B,
     1 40B,40B,40B,40B,40B,140B,72B,43B,100B,47B,
     1 75B,42B,40B,141B,142B,143B,144B,145B,146B,147B,
     1 150B,151B,40B,40B,40B,40B,40B,40B,152B,153B,154B,
     1 155B,156B,157B,160B,161B,162B,40B,40B,40B,40B,40B,
     1 40B,176B,163B,164B,165B,166B,167B,170B,171B,172B,
     1 40B,40B,40B,133B,40B,40B,40B,40B,40B,40B,40B,40B,
     1 40B,40B,40B,40B,135B,40B,40B,173B,101B,102B,103B,
     1 104B,105B,106B,107B,110B,111B,40B,40B,40B,40B,40B,
     1 175B,112B,113B,114B,115B,116B,117B,120B,121B,122B,
     1 40B,40B,40B,40B,40B,40B,134B,40B,123B,124B,125B,126B,
     1 127B,130B,131B,132B,40B,40B,40B,40B,40B,60B,61B,
     1 62B,63B,64B,65B,66B,67B,70B,71B,174B,40B,40B,40B,40B,40B/
      IF (NO.EQ.0) GOTO 6
```

```fortran
      DO 8 I=1,NO
        TEMP1=BUFF(I)
        HIGH = ISHFT(TEMP1,-8)
        LOW  = ISHFT(HIGH,8)
        LOW  = TEMP1 - LOW
        CALL OTOD(HIGH)
        CALL OTOD(LOW)
        CD1=ASC(HIGH)
        CD2=ASC(LOW)
        BUFF(I)=ISHFT(CD1,8)+CD2
8     CONTINUE
6     RETURN

      END

C THE FOLLOWING SUBROUTINE CONVERTS AN OCTAL NUMBER TO A DECIMAL NUMBER

      SUBROUTINE OTOD(NUM)
      INTEGER NUM,J,N,R
      J = NUM
      J = J/100B
      N = J*64
      R = NUM - J*100B
      J = R/10B
      N = N + J*8
      R = R - J*10B
      NUM = N + R
      RETURN
      END
```

```
FTN4

      SUBROUTINE RCD(BUFF,NO)

C THE FOLLOWING SUBROUTINE ACCEPTS AN ARRAY OF WORDS STORED IN "BUFF" AND AN
C INTEGER "NO" REPRESENTING THE NUMBER OF WORDS IN BUFF.   EACH WORD CONTAINS
C TWO CHARACTERS IN RCD CODE REPRESENTED IN STANDARD FORMAT WHICH ARE BROKEN
C DOWN INTO SEPARATE RCD CODES, CONVERTED TO ASCII CODE BY MEANS OF A TABLE,
C AND THEN STORED TWO CHARACTERS PER WORD IN THE STANDARD FORMAT BACK IN THE
C THE ARRAY BUFF FROM WHERE IT WAS TAKEN

      INTEGER RCT(63),BUFF(9950),NO,I,NEW,TEMP1,TEST
C THE LARGEST ARRAY ACCEPTED BY THE SUBROUTINE RCD IS 9950
      INTEGER CD1,CD2
      DATA RCT/061B,062B,063B,064B,065B,064B,067B,070B,
     1         071B,060B,043B,100B,072B,076B,075B,040B,
     1         057B,123B,124B,125B,126B,127B,130B,131B,
     1         132B,137B,054B,050B,047B,134B,042B,055B,
     1         112B,113B,114B,115B,116B,117B,120B,121B,
     1         122B,041B,044B,052B,135B,073B,045B,053B,
     1         101B,102B,103B,104B,105B,106B,107B,110B,
     1         111B,077B,056B,051B,133B,074B,136B/
      IF (NO.EQ.0) GOTO 6
      DO 8 I=1,NO
         TEMP1=BUFF(I)
         NEW=40000B
5        NEW=NEW-400B
         TEST=TEMP1-NEW
         IF (TEST.GE.000B) GOTO 3
         GOTO 5
```

```
C  TEST IF THE VALUE OF THE SECOND BCD CODE NUMBER
C  NEW IS THE FIRST BCD CODE NUMBER TO BE SHIFTED RIGHT 8 BITS
3     NEW=ISHFT(NEW,-8)
      CD1=BCT(NEW)
      CD2=BCT(TEST)
C  CD1 AND CD2 CONTAIN THE ASCII EQUIVALENTS OF NEW AND TEST
      BUFF(I)=ISHFT(CD1,8)+CD2
8     CONTINUE
6     RETURN
      END
```

APPENDIX D

PROGRAM TSTAPE


```
Display start up message on the console
Repeat

      Move the cursor to line 22
      Read in the desired command
      If not a valid command
      then

            Display error message

      else

            If the drive has not yet been initialized
            then

                  Display error message

            else

                  Move cursor to line 22
                  Turn memory lock on
                  Case Command of

                        In: Initialize the tape drive
                            Call TAPTRN (KODE = -1)
                            Display Status

                        SH: Show the contents of the first record of each file
                            End-of-volume = False
                            Move cursor to line 22
                            Determine the format the record is to be displayed in
                            Rewind the tape
                            Repeat

                                    Read a record
                                    If EOV encountered
                                    then

                                          End-of-volume = True

                                    endif
                                    If not EOV
                                    then
```

```
                    Write out number of words transferred
                    Display record of format desired
                    While not EOF

                         Read next record

                    Endwhile
               endif

          Until EOV
          Display status

     RD: Read a record
          Move cursor to line 22
          Read in the number of words to be read
            (Default is 9950 words)
          Initialize buffer to zeroes
          Call TAPTRN (Kode = 8)
          Move cursor to line 22
          If end of file marker read
          then

               Display appropriate message

          else

               Determine if buffer read is to be dumped to the
               line printer
               If buffer is to be dumped
               then

                    Move cursor to line 22
                    Turn off memory lock
                    If ASCII output desired
                    then
                         Output data
                         Display status

                    endif
                    If Integer output desired
                    then
                         Output data
                         Display status

                    endif
                    If Octal output desired
                    then
                         Output data
                         Display status

                    endif
                    If EBCDIC output desired
                    then
                         Call EBCDIC
                         Output converted ASCII data
                         Display status
```

```
                         endif
                         If BCD output desired
                         then
                              Call BCD
                              Output converted ASCII data
                              Display status

                         endif
                         else
                              Display status

                         endif

WT: Write a record
    Move cursor to line 22
    Determine number of words in the record that are
      to be written
    Determine starting place in the write buffer
    Call TAPTRN (KODE = 9)

DI: Display the read buffer
    Move cursor to line 22
    Determine which form of output is desired
    If ASCII output desired
    then
         Output data
         Display status

    endif
    If Integer output desired
    then
         Output data
         Display status

    endif
    If Octal output desired
    then
         Output data
         Display status

    endif
    If EBCDIC data desired
    then
         Call EBCDIC
         Output converted ASCII data
         Display status

    endif
    If BCD output desired
    then
         Call BCD
         Output converted ASCII data
         Display status

    endif
```

ST: Status of the drive
    Turn off memory lock
    Display status of the last command

SL: Set record length
    Move cursor to line 22
    Read in desired record length
    Display status

RW: Rewind tape
    Call TAPTRN (Kode = 1)
    Display status

NR: Number of records in a file
    If not (BOT) or
       not (EOF) display
       error message
    endif
    Record counter = 0, EOF = False
    Repeat

        Call TAPTRN (Kode = 8)
        If end of file has been reached
        then

            Display the number of records read and the
              length of the last data record read
            EOF = True

        else

            Increment record counter

        endif

    Until EOF = True
    Display status

SK: Skip to end of file
    Move cursor to line 22
    Determine if record or file skip
    Determine number of records/files to skip
    If record skip
    then

        Kode = 3

    else

        Kode = 5

    endif
    If number of records/files to skip < 0
    then

        Kode = Kode +1
        Number of records/files to skip =
        -(Number of records/files to skip)

```
        endif
        Call TAPTRN (Kode)
        Display status

RL: Record length
    Call TAPTRN (Kode = 8)
    Move cursor to line 22
    Display the number of words read
    Display status

EF: Write End of File marker
    Call TAPTRN (2)
    Display status

TS: Test Read/Write Pattern
    Move cursor to line 22
    Determine length of record to write
    Determine the number of records to be written
    Determine if buffer dumps desired
    For I=1 to Number of records to be written

        If buffer dumps desired
        then

            Output buffer in appropriate form

        endif
        Call TAPTRN (Kode = 9)
        Increment length of record to write

    Endfor
    Call TAPTRN (Kode = 2)
    Call TAPTRN (Kode = 2)
    Call TAPTRN (Kode = 1)
    For I=1 to Number of records to be read

        Call TAPTRN (Kode = 8)
        If buffer dumps desired
        then

            Output buffer in appropriate form

        endif
        Increment length of record to read

    Endfor
    Call TAPTRN (Kode = 1)

EX: Exit
    Turn off memory lock
    Call TAPTRN (Kode = -2)
    Halt

HE: Help facility
    Open external file
    Read command summary for external file
    Close file
```

```
        End Case (of commands)
        endif (valid command)
      Until Exit command chosen

End Program TSTAPE
```

SUBROUTINE TIME

```
c   The following subroutine gets the current system time.
c   This subroutine is used in order that all messages displayed on the
c   console to the user are present for 2 seconds.

    Subroutine TIME

        Obtain the current system time
        Sec = current second
        Difference = 0
        Repeat

            Obtain current system time
            Difference = current second - Sec

        Until difference > 2
        Return

End Subroutine TIME
```

SUBROUTINE BCD (BUFF, NO)

```
c   The following subroutine converts an array of BCD characters to their
c   corresponding ASCII characters.
c   The characters to be converted are input in BUFF and the number of
c   characters to convert are input in NO.
    If there are characters to convert
    then

        For I=1 to NO

            Temp = BUFF(I)
            Get the upper 8 bits and shift left
            Look up this number in the table for ASCII equivalent
            Get lower 8 bits and look up the ASCII equivalent
            Store the ASCII equivalent back into BUFF(I)

        Endfor

    endif

End Subroutine BCD
```

SUBROUTINE &EBCDIC (BUFF,NUMBER)

```
c   The following subroutine accepts an array of words, BUFF, (maximum size
c   9950) coded in EBCDIC and converts each word to ASCII code.  The size
c   of the array is passed through the parameter "NUMBER" and the resultant
c   ASCII code is passed back through the parameter "BUFF".
    If NUMBER > 0
    then

        For I=1 TO NUMBER DO
```

```
            TEMP = BUFF(I)
            HIGH = TEMP SHIFTED RIGHT 8 BITS
            LOW = HIGH SHIFTED LEFT 8 BITS
            LOW = TEMP-LOW
            CONVERT HIGH TO A DECIMAL NUMBER
            CONVERT LOW TO A DECIMAL NUMBER
            CONVERT1 = ASCII EQUIVALENT OF EBCDIC HIGH
            CONVERT2 = ASCII EQUIVALENT OF EBCDIC LOW
            BUFF(I) = CONVERT1 SHIFTED LEFT 8 BITS + CONVERT2
        Endfor

    endif
    Return

End Subroutine



SUBROUTINE &KLOAD (Row,Column)

c   This subroutine moves the cursor to the desired row and column.
c   These values are given in the input parameters Row and Column.

        Clear Buffer
        Encode the octal commands for moving the cursor to the
          desired position into Buffer
        Write out Buffer to the screen
        Return

End Subroutine
```

RTAPE   T=00004 IS ON CR SY   USING 00002 BLKS R=0000

```
0001    :**This transfer file compiles the TAPTN program.
0002    :RU,FLECS,&TAPTRN,&TAPE::13,TAPE::13
0003    :RU,FTN4X,&TAPE::13,1,ZTAPTRN::13
```

CTSTAP T=00004 IS ON CR00013 USING 00002 BLKS R=0000

```
0001    :**This transfer file compiles the TSTAPE program and the BCD and
0002    :**EBCDIC subroutines.  Then it links all together with the TAPTRN routine.
0003    :OF,TSTAE,8
0004    :RU,FTN4X,&BCD::13,1,ZBCD::13
0005    :RU,FTN4X,&EBCDIC::13,1,ZEBCDIC::13
0006    :RU,FTN4X,&TSTAPE,1,ZTSTAPE::13
0007    :RU,LOADR,LTSTAPE
```

LTSTAP T=00004 IS ON CR00013 USING 00002 BLKS R=0000

```
0001    RE,ZTSTAPE::13
0002    RE,ZKLOAD::13
0003    RE,ZTAPTRN::13
0004    RE,ZBCD::13
0005    RE,ZEBCDIC::13
0006    EN
```

APPENDIX E

TRANSFER FILES TO COMPILE AND LOAD THE PROGRAM

DOCUMENT CONTROL DATA – R & D

(Security classification of title, body of abstract and indexing annotation must be entered when the overall document is classified)

1 ORIGINATING ACTIVITY DEFENCE RESEARCH ESTABLISHMENT OTTAWA Department of National Defence Ottawa, Ontario, K1A 0Z4, Canada	2a. DOCUMENT SECURITY CLASSIFICATION Unclassified
	2b. GROUP

3. DOCUMENT TITLE

TAPTRN – A TAPE UTILITY PROGRAM

4. DESCRIPTIVE NOTES (Type of report and inclusive dates)
Technical Note

5. AUTHOR(S) (Last name, first name, middle initial)

SLINN, Suzanne Y.

6. DOCUMENT DATE April 1984	7a. TOTAL NO. OF PAGES 55	7b. NO. OF REFS
8a. PROJECT OR GRANT NO. 33X00	9a. ORIGINATOR'S DOCUMENT NUMBER(S) DREO TN 83-38	
8b. CONTRACT NO.	9b. OTHER DOCUMENT NO.(S) (Any other numbers that may be assigned this document)	

10. DISTRIBUTION STATEMENT

Unlimited

11. SUPPLEMENTARY NOTES	12. SPONSORING ACTIVITY DREO

13. ABSTRACT

The computer program TAPTRN, a utility routine used to read magnetic tapes of unknown content and format, is described for use on the HP 1000 computer. It provides the user ready access to all the capabilities of the tape handling hardware of the HP 1000. TAPTRN is documented in terms of a brief description of the utility, its capabilities, a guide on how to use it, and the source and pseudocode for the routine written.

58

KEY WORDS

SOFTWARE

MAGNETIC TAPE

FORTRAN

HP 1000 COMPUTER

FLECS

INSTRUCTIONS

1. ORIGINATING ACTIVITY: Enter the name and address of the organization issuing the document.

2a. DOCUMENT SECURITY CLASSIFICATION: Enter the overall security classification of the document including special warning terms whenever applicable.

2b. GROUP: Enter security reclassification group number. The three groups are defined in Appendix 'M' of the DRB Security Regulations.

3. DOCUMENT TITLE: Enter the complete document title in all capital letters. Titles in all cases should be unclassified. If a sufficiently descriptive title cannot be selected without classification, show title classification with the usual one-capital-letter abbreviation in parentheses immediately following the title.

4. DESCRIPTIVE NOTES: Enter the category of document, e.g. technical report, technical note or technical letter. If appropriate, enter the type of document, e.g. interim, progress, summary, annual or final. Give the inclusive dates when a specific reporting period is covered.

5. AUTHOR(S): Enter the name(s) of author(s) as shown on or in the document. Enter last name, first name, middle initial. If military, show rank. The name of the principal author is an absolute minimum requirement.

6. DOCUMENT DATE: Enter the date (month, year) of Establishment approval for publication of the document.

7a. TOTAL NUMBER OF PAGES: The total page count should follow normal pagination procedures, i.e., enter the number of pages containing information.

7b. NUMBER OF REFERENCES: Enter the total number of references cited in the document.

8a. PROJECT OR GRANT NUMBER: If appropriate, enter the applicable research and development project or grant number under which the document was written.

8b. CONTRACT NUMBER: If appropriate, enter the applicable number under which the document was written.

9a. ORIGINATOR'S DOCUMENT NUMBER(S): Enter the official document number by which the document will be identified and controlled by the originating activity. This number must be unique to this document.

9b. OTHER DOCUMENT NUMBER(S): If the document has been assigned any other document numbers (either by the originator or by the sponsor), also enter this number(s).

10. DISTRIBUTION STATEMENT: Enter any limitations on further dissemination of the document, other than those imposed by security classification, using standard statements such as:

(1) "Qualified requesters may obtain copies of this document from their defence documentation center."

(2) "Announcement and dissemination of this document is not authorized without prior approval from originating activity."

11. SUPPLEMENTARY NOTES: Use for additional explanatory notes.

12. SPONSORING ACTIVITY: Enter the name of the departmental project office or laboratory sponsoring the research and development. Include address.

13. ABSTRACT: Enter an abstract giving a brief and factual summary of the document, even though it may also appear elsewhere in the body of the document itself. It is highly desirable that the abstract of classified documents be unclassified. Each paragraph of the abstract shall end with an indication of the security classification of the information in the paragraph (unless the document itself is unclassified) represented as (TS), (S), (C), (R), or (U).

The length of the abstract should be limited to 20 single-spaced standard typewritten lines; 7½ inches long.

14. KEY WORDS: Key words are technically meaningful terms or short phrases that characterize a document and could be helpful in cataloging the document. Key words should be selected so that no security classification is required. Identifiers, such as equipment model designation, trade name, military project code name, geographic location, may be used as key words but will be followed by an indication of technical context.

END

FILMED

4-85

DTIC